

Ref.	HAV130-13 series 3
Issue	1
Date	Oct 2009
Page	1 of 2

## Hillstone – VARICON- automatic constant current DC load bank

Type ref **HAV130-13 series3**

- Automatic range selection
- Lead Acid or Ni-cad battery testing
- Automatic constant current control
- Wide battery voltage range 12V to 130V DC
- Simple operation via remote hand held controller
- Auto stop on time and battery voltage
- Digital LCD display
- Safety isolation contactors
- Fan fail protection
- High power up to 13KW
- Cables included
- Portable
- Computer interface option



13 KW unit illustrated

The Hillstone **HAV 130-13 series3** load bank is designed for automatic constant current DC battery discharge testing for a wide range of lead acid and ni-cad batteries and incorporates the unique Hillstone VARICON remote hand held controller which provides a cost effective solution to fully automatic load banks.

All units incorporate light weight, force cooled high power resistor elements and several safety features including reverse polarity connection, high battery volts, fan fail, auto shut-down, emergency stop push button and battery isolation of each load circuit via continuously rated DC contactors. The unit also includes automatic battery voltage selection, thereby eliminating incorrect operator use.

Load bank operation - The unit should be connected to a 240V ( 110V optional ) single phase auxiliary mains supply and also to the battery . On power up, the load bank will carry out a self diagnostic check to ensure the equipment is functioning correctly and also check the battery is connected correctly and the battery voltage is within the operating limits of the load bank design. The load bank will then automatically select the appropriate internal circuits which are compatible with the connected battery.

The operator then enters the required stop voltage and discharge time period, followed by the discharge current before commences the test by pressing the START push button. The battery voltage, load current and elapse time is displayed on the remote hand held

controller during the test. The load bank will automatically maintain the load current constant as the battery voltage falls. When the battery voltage falls to the end of discharge voltage ( or pre-set time period ) the test will stop by automatic disconnection via internal contactors. The display of elapse time and amperhours discharged will be frozen on the LCD screen. The test can be terminated at any time by pressing the STOP push button. The load bank also incorporates a PAUSE button which allows the test to be stopped and then re-started without re-setting all the test parameters. The elapse time and amperhours readings will also re-start without resetting to zero. This feature enables operators to remove faulty cells during the test if required.

Ref.	HAV130-13 series3
Issue	1
Date	Oct 2009
Page	2 of 2

## Specification

Type ref	HAV130-13 series3				
Nominal DC voltage ranges	6V	12V	24V	50V	110V
Max. DC voltages	8V	16V	32.5V	65V	130V
Max. DC currents	50A	100A	200A	200A	100A
Max power rating	400W	1600W	6500W	13KW	13KW
Max. No. lead acid cells	3	6	15	30	60
Max. No. Ni-cad cells	6	12	22	42	96
Constant current performance ( rating dependant on voltage)	33A at 5.4V	67A at 10.8V	130A at 21V	133A at 43V	73A at 95V
Load current adjustment	less than 1 amp to max current				
Digital Panel Display	4 line 20 character numerical backlit display				
Display information	Battery volts		Battery current	Elapse time	
	Discharged Ampere hours			Test status / fault	
Auxiliary mains supply	240V single phase 50 hz				
Mains cable set	2 metre mains cable with IEC socket & UK 13A plug				
DC cable set	3 metre twin, flexible cable set with industrial plug/socket				
Hand held controller cable	5 metres ( longer available on request )				
Case size	1000mm long x 500mm wide x 700mm high ( + 50 mm handles )				
Weight	50 kgs				
Finish	Light grey RAL7032 textured finish				
Environmental protection rating	IP21				
Movement	Swivel castors and top handles				
Operating temperature range	0 – 40 deg C				
Storage temperature range	0 – 80 deg C				

### Notes

- 1) Units are designed for indoor use only in a clean, dry and well ventilated environment.
- 2) The available constant current and ratings are proportional to the end of test voltage.
- 3) Information in technical literature, quotations or data sheets are intended to be correct at the time of publication. Hillstone Products Ltd bears no responsibility for the accuracy of any information given.
- 4) We reserve the right to make detail changes to specification, components, dimensions or weights at the time of design or manufacture without prior notice.
- 5) All information in this data sheet is the copyright of Hillstone Products Ltd.
- 6) All designs and software is the intellectual property of Hillstone Products Ltd

### Optional extras

1. 110V auxiliary mains supply
2. Computer interface to transfer battery data to a laptop computer.
3. Extra length battery cables

Hillstone Products Ltd  
 Unit 2 Portland Industrial Estate  
 Portland Street, Bury  
 Lancashire England BL9 6EY

Tel. +44 (0) 161 763 3100  
 Fax. +44 (0) 161 763 3158  
 e-mail sales@hillstone.co.uk  
 www.hillstone.co.uk